

Load Disconnect Switches and Motor Starters



Safety switch

80 A

8146/5-V37-307-00-1510 Art. No. 226357



- Can be used with conventional drives and drives controlled by frequency converters
- Intelligent design: A single rotary actuator for actuating both main and auxiliary contacts, ≥ 20 ms leading auxiliary contact for safely disconnecting the frequency converter
- Version complies with IEC/EN 62626-1, Class 1
- The rotary actuator can be locked with 3 padlocks in the 0-position

MY R. STAHL 8146L



R. STAHL's 8146/5-V37 series safety switches safely disconnect the power supply to machinery and system components for cleaning and repair as prescribed. All of the installed load disconnect switches have an AC-3 switching capacity. The switches can be locked in the 0-position using padlocks.

Technical Data

Explosion Protection

Scope of validity	European Union (ATEX) IECEX
Application range (zones)	1 2 21 22
IECEX gas certificate	IECEX PTB 06.0090
IECEX gas explosion protection	Ex db eb IIC T4 Gb
IECEX dust certificate	IECEX PTB 06.0090
IECEX dust explosion protection	Ex tb IIIC T130 °C Db
ATEX gas certificate	PTB 01 ATEX 1024
ATEX gas explosion protection	Ex II 2 G Ex db eb IIC T4 Gb
ATEX dust certificate	PTB 01 ATEX 1024
ATEX dust explosion protection	Ex II 2 D Ex tb IIIC T130 °C Db
Certificates	ATEX (PTB), China (NEPSI), IECEX (PTB), India (PESO), Korea (KGS)
Declaration of Conformity	ATEX (EUK), China (CCC)
Notes	Product label may vary. Series devices have certification according to ATEX and IECEX.

Electrical Data

Rated operational voltage AC	500 V
Rated operational current	80 A
Switching capacity AC-3 230 V	22 kW
Switching capacity AC-3 400 V	45 kW
Switching capacity AC-3 440 V	45 kW
Switching capacity AC-3 500 V	55 kW
Auxiliary contact NC	without
Auxiliary contact NO	without
Frequency range	50 – 60 Hz

Load Disconnect Switches and Motor Starters



Safety switch

80 A

8146/5-V37-307-00-1510 Art. No. 226357

Ambient Conditions

Note	Information regarding ambient conditions can be found on the Internet at r-stahl.com. MY R. STAHL 8146L
------	---

Ambient conditions

Ambient conditions	Number of poles		max. current (A)	Conductor cross-section ¹⁾ (mm ²)		Temperature class / perm. ambient temperature
	Main contacts	Auxiliary contact		min.	max.	
	3	0	80	50	150	T4: -40 ... +60 °C

¹⁾ Project engineering note:

The maximum conductor cross-sections given were determined using the H07V.

The minimum bending radius was assumed to be 4 x outer diameter in accordance with VDE 0298-3.

²⁾ only with heat-resistant conductor > 70 °C at cable entries and/or > 85 °C at clamping units

Bold: Observe information on the type plate

Mechanical Data

Degree of protection (IP)	IP66
Degree of protection note	acc. to EN/IEC 60529
Enclosure material	Polyester resin, Glass fibre reinforced
Additional terminal	Main contact on terminals
Min. solid conn. cr.-sect. AWG	AWG 1
Connection terminal auxiliary contact min. AWG	AWG 16
Connection cross section	4 ... 6 mm ²
Auxiliary connection connection terminals	0.75 ... 2.5 mm ²
Connection cross-section note	Depending on the application, for more detailed information see operating instructions at r-stahl.com
Construction type	Standard
Dimension A	681.5 mm
Dimension A inch	26.83 in
Dimension B	340.5 mm
Dimension B inch	13.41 in
Dimension C	195 mm
Dimension C inch	7.68 in
Handle colour	Yellow shroud, red handle
Seal	Silicone, foamed
Lockable in	Three times in 0 position
Detailed number of poles	3-pole
Weight	14.4 kg
Weight	31.75 lb

Components

Entry type	Standard 8161, moulded material
Cable gland	2 x M63 Ø 28 to 48 mm 1 x M20 Ø 4 to 13 mm

Load Disconnect Switches and Motor Starters




Safety switch

80 A


8146/5-V37-307-00-1510 Art. No. 226357

Technical Drawings – Subject to Alterations



81..V..3.-00..
3-pole

Dimensional Drawings (All Dimensions in mm [inches]) – Subject to Alterations



Accessories

Auxiliary contact



2 NC (8080/1-3)
250 V AC/DC
Max. 6 A
1.5 to 2.5 mm², solid/finely stranded
The switching function of the auxiliary contact depends on the installation slot used.
Left and right: Synchronising

Art. No.

168356

1 NC + 1 NO (8080/1-1)
250 V AC/DC
Max. 6 A
1.5 to 2.5 mm², solid/finely stranded
The switching function of the auxiliary contact depends on the installation slot used.
Left: Delayed (ON), leading (OFF)
Right: Synchronising

168351

2 NO (8080/1-4)
250 V AC/DC
Max. 6 A
1.5 to 2.5 mm², solid/finely stranded
The switching function of the auxiliary contact depends on the installation slot used.
Left and right: Synchronising

168353

Spare Parts

Auxiliary contact key



For removing installed auxiliary contacts

Art. No.

201909

We reserve the right to make alterations to the technical data, dimensions, weights, designs and products available without notice. The illustrations cannot be considered binding.