

8174/103-2413-22 Art. No. 139345



- Power supply in Ex d enclosures
- One to 72 cores are combined in one conductor bushing
- Versions: Screwable, pluggable
- For voltages up to max. 1000 V
- For conductor cross-sections up to 70 mm²

MY R. STAHL 8174A



The conductor bushings are used to connect the conductors between enclosures with the "flame-proof" and "increased safety" types of protection. The cores are moulded with high-quality, leakage-current-resistant PU resin, meaning that they are insulated from the enclosure wall.

Technical Data

Explosion Protection

Application range (zones)	1, 2
IECEX gas certificate	IECEX PTB 06.0081U
IECEX gas explosion protection	Ex db IIC Gb
IECEX firedamp protection	Ex db I Mb
ATEX gas explosion protection	Ⓔ II 2 G Ex db IIC Gb
ATEX firedamp protection	Ⓔ I M2 Ex db I Mb
Certificates	ATEX (PTB), China (CQST), IECEX (PTB)

Electrical Data

AC rated operational voltage	750 V
Rated operational current	6 A
Rated operational current	6 A

Ambient Conditions


Ambient temperature	-40 °C ... +110 °C
---------------------	--------------------

Mechanical Data

Ex d conductor length	2500 mm
Ex e conductor length	2500 mm
Min. conductor cross section	0.5 mm ²
Number of core ends	24
Thread size	M33
Thread pitch	1,5
Cable colour	Black
Weight	4.85 kg
Weight	10.68 lb

8174/103-2413-22 Art. No. 139345

Technical Drawings – Subject to Alterations



Accessories

Jam nut

Art. No.



M33 x 1.5

108375

We reserve the right to make alterations to the technical data, dimensions, weights, designs and products available without notice. The illustrations cannot be considered binding.