

8174/104-0606-11 Art. No. 139788



- Power supply in Ex d enclosures
- One to 72 cores are combined in one conductor bushing
- Versions: Screwable, pluggable
- For voltages up to max. 1000 V
- For conductor cross-sections up to 70 mm<sup>2</sup>

MY R. STAHL 8174A




The conductor bushings are used to connect the conductors between enclosures with the "flame-proof" and "increased safety" types of protection. The cores are moulded with high-quality, leakage-current-resistant PU resin, meaning that they are insulated from the enclosure wall.

### Technical Data

<b>Explosion Protection</b>	
Application range (zones)	1, 2
IECEX gas certificate	IECEX PTB 06.0081U
IECEX gas explosion protection	Ex db IIC Gb
IECEX firedamp protection	Ex db I Mb
ATEX gas explosion protection	Ⓔ II 2 G Ex db IIC Gb
ATEX firedamp protection	Ⓔ I M2 Ex db I Mb
Certificates	ATEX (PTB), China (CQST), IECEX (PTB)
<b>Electrical Data</b>	
AC rated operational voltage	750 V
Rated operational current	45 A
Rated operational current	45 A
<b>Ambient Conditions</b>	
Ambient temperature	-40 °C ... +110 °C
<b>Mechanical Data</b>	
Ex d conductor length	1000 mm
Ex e conductor length	1000 mm
Min. conductor cross section	10 mm <sup>2</sup>
Number of core ends	6
Thread size	M42
Thread pitch	1,5
Cable colour	Black
Weight	1.49 kg
Weight	3.29 lb

8174/104-0606-11 Art. No. 139788

### Technical Drawings – Subject to Alterations



## Accessories

### Jam nut

### Art. No.



M42 x 1.5

108378

We reserve the right to make alterations to the technical data, dimensions, weights, designs and products available without notice. The illustrations cannot be considered binding.