

8174/104-0309-11 Art. No. 139910



- Current lead-in for Ex d enclosures
- 1 to 72 conductors combined in one current lead-in
- Series: screw-in, plug-in
- For voltages up to max. 1000 V
- For size conductor up to 70 mm²

WebCode 8174A



The conductor bushings are used to provide the wire connection between „flameproof“ enclosures and „increased safety“ enclosures.

The conductors are potted with high-quality, creepage-resistant PU-resin and are thus insulated from the enclosure wall.

Technical Data

Explosion Protection

Application range (zones)	1 2
IECEX gas certificate	IECEX PTB 06.0081U
IECEX gas explosion protection	Ex db IIC Gb
IECEX firedamp certificate	IECEX PTB 06.0081U
IECEX firedamp protection	Ex db I Mb
ATEX gas certificate	PTB 01 ATEX 1065 U
ATEX gas explosion protection	Ⓔ II 2 G Ex db IIC Gb
ATEX firedamp certificate	PTB 01 ATEX 1065 U
ATEX firedamp protection	Ⓔ I M2 Ex db I Mb
Certificates	ATEX (PTB), EAC (ENDCE), IECEX (PTB)

Ambient Conditions




Ambient temperature	-40 °C ... +110 °C
---------------------	--------------------

Mechanical Data

Ex d conductor length	1000 mm
Ex e conductor length	1000 mm
Min. conductor cross section	35 mm ²
Number of core ends	3
Thread size	M42
Thread pitch	1,5
Cable colour	Black
Weight	2.283 kg
Weight	5.03 lb

8174/104-0309-11 Art. No. 139910

Technical Drawings – Subject to Alterations



We reserve the right to make alterations to the technical data, dimensions, weights, designs and products available without notice. The illustrations cannot be considered binding.